


Lutron Dvcl 153p Installation Instructions

LUTRON 

Dimmer 153P, 153P, 153P, 153P

Please read before installing.

English

DVCL-153P, DVWCL-153P, SCL-153P, DVSCCL-153P, LECL-153P, CTCL-153P
120 V~ 60 Hz
120 W
CFL, LED

DVCL-253P, DVSCCL-253P
120 V~ 60 Hz
250 W
CFL, LED

If using LED or CFL bulbs, they must be Lutron compatible for optimal performance!
For the compatible bulb list, please visit www.lutron.com/Dimcflled

Help

Use our mobile friendly self-paced installation tool:
www.lutron.com/wiringwizard

Find more product information:
www.lutron.com/support

- Videos
- Frequently Asked Questions
- Online Chat (9 am-5 pm EST)

Call us:
U.S.A. (Canada/Continental)
1.844.LUTRON1 (S.A. 7687) (24/7)
Mexico
+1.888.235.2915
Others
+1.810.262.3300


IMPORTANT

- CAUTION:** Use only with permanently installed fixtures with dimmable screw-in compact fluorescent, dimmable screw-in LED, halogen, or incandescent bulbs. Do not use on corded appliances, motor-driven appliances, or transformer-supplied appliances.
- Install in accordance with all national and local electrical codes.
- Always "grounding-neutral" wires within the wallbox for an existing switch or dimmer. The National Electrical Code (NEC) allows a switch/dimmer to be installed as a replacement as long as it is nonmetallic, noncombustible, and is used with nonmetallic attachment screws or if the circuit is protected by a ground fault circuit interrupter. Lutron switches meet this requirement. When installing a control according to these methods, cap or remove green wire before connecting control into wallbox.
- Only one dimmer can be used in a 3-way circuit.
- Protect the dimmer from dust and oil when painting or sanding the wall.
- It is normal for the dimmer to feel warm to the touch during operation.
- Clean the dimmer with a soft damp cloth only. Do not use any chemical cleaners.
- For indoor use only.

Limited Warranty:
Lutron and CFL are trademarks of Lutron Electronics Co., Inc. registered in the U.S. and other countries.
©2015-2017 Lutron Electronics Co., Inc.

www.lutron.com/support

1 Turn power OFF at circuit breaker



WARNING: SHOCK HAZARD.
May result in serious injury or death. Turn off power at circuit breaker or fuse before installing.

2 Remove side sections if mounting two or more devices side by side

Remove side sections if mounting two or more devices side by side. Removing side sections reduces the dimmer's maximum wattage rating (see chart below).

NOTE: Maximum wattage ratings are not affected when using CFL, LEDs or CFLs.


Maximum Allowable Incandescent/Halogen Wattage		
No side removed	1 side removed	2 sides removed
120 W	60 W	30 W

*For maximum wattage information when mixing light bulb loads see www.lutron.com/Dimcflled

3 Determine wiring type

For lights switched from **one** location:

3A




↓ Use wiring diagram 4A below ↓

OR

For lights switched from **two** locations:

3B **NOTE:** Only one dimmer can be used per circuit.




IMPORTANT! Top or bottom the dimmer wire. This is usually connected to a dimmer or different colored wire than the others. This dimmer will exclude the ground screw.

↓ Use wiring diagram 4B below ↓

4 Remove existing device and connect the new dimmer (appropriately choose 4A or 4B diagram below)

For lights switched from **one** location:


4A



OR


For lights switched from **two** locations:

4B




NOTE: This dimmer shown for illustration purposes. Other products may vary.

5 Mount the dimmer using the provided screws



6 Turn power ON at circuit breaker




7 Adjust dimming range for LEDs and CFLs

A) Turn lights OFF using the dimmer's (ON/OFF) switch.

B) Move the dimming slider to the minimum (left) position of travel.

C) Turn the adjustment dial until the lights are visible. **NOTE:** The adjustment dial on your dimmer may be in a different location than others.

D) Dimmer range operation using the toggle (push up if necessary).



8 Install the faceplate (not included)

9 Installation is complete!

Troubleshooting

Symptom	Solution
CFLs or LEDs do not dim. Test a basic dimming range, or try a "Warm-to-Hot" dimmable CFL or LED bulb.	Verify Step 1 . Ensure bulbs are Lutron compatible.
Dimmer is working, but some bulbs do not dim.	Dimmable range is different bulb.
One dimmer will not turn on if the other location is turned off.	Common dimmer wire transfer wires are swapped. Verify Step 4B .

For additional Troubleshooting, please visit www.lutron.com/support

LUTRON DVCL-153P INSTALLATION INSTRUCTIONS: THE LUTRON DVCL-153P IS A VERSATILE DIMMER SWITCH DESIGNED FOR COMPATIBILITY WITH A WIDE RANGE OF LIGHTING TYPES, INCLUDING INCANDESCENT, HALOGEN, AND CERTAIN TYPES OF DIMMABLE LED AND CFL BULBS. THIS GUIDE WILL PROVIDE YOU WITH STEP-BY-STEP INSTRUCTIONS ON HOW TO INSTALL THIS DIMMER SWITCH SAFELY AND EFFICIENTLY, ENSURING YOU ENJOY THE BENEFITS OF ADJUSTABLE LIGHTING IN YOUR HOME.

SAFETY PRECAUTIONS

BEFORE STARTING YOUR INSTALLATION, IT'S CRUCIAL TO TAKE SEVERAL SAFETY PRECAUTIONS TO ENSURE YOUR SAFETY AND THE PROPER FUNCTIONING OF THE DIMMER SWITCH:

1. TURN OFF POWER: LOCATE YOUR CIRCUIT BREAKER AND TURN OFF THE POWER SUPPLY TO THE LIGHT FIXTURE YOU WILL BE WORKING ON. CONFIRM THAT THE POWER IS OFF BY USING A VOLTAGE TESTER.

2. **WEAR SAFETY GEAR:** USE SAFETY GOGGLES AND GLOVES TO PROTECT YOURSELF FROM ANY ACCIDENTAL ELECTRICAL SHOCKS OR INJURIES DURING THE INSTALLATION PROCESS.
3. **READ INSTRUCTIONS THOROUGHLY:** FAMILIARIZE YOURSELF WITH THE LUTRON DVCL-153P MANUAL AND INSTALLATION INSTRUCTIONS BEFORE BEGINNING.
4. **CHECK COMPATIBILITY:** ENSURE THAT YOUR EXISTING LIGHT FIXTURES AND BULBS ARE COMPATIBLE WITH THE LUTRON DVCL-153P. REFER TO THE MANUFACTURER'S SPECIFICATIONS FOR THE SUPPORTED LOAD TYPES.

TOOLS AND MATERIALS NEEDED

BEFORE YOU BEGIN THE INSTALLATION, GATHER THE FOLLOWING TOOLS AND MATERIALS:

- LUTRON DVCL-153P DIMMER SWITCH
- SCREWDRIVER (FLAT-HEAD AND PHILLIPS)
- WIRE STRIPPER
- VOLTAGE TESTER
- ELECTRICAL TAPE
- WIRE NUTS (IF NOT INCLUDED WITH THE DIMMER)
- LEVEL (OPTIONAL)

PREPARING FOR INSTALLATION

BEFORE YOU INSTALL THE LUTRON DVCL-153P, IT'S ESSENTIAL TO PREPARE THE WORKSPACE:

1. **REMOVE THE EXISTING SWITCH:**
 - USE YOUR SCREWDRIVER TO REMOVE THE FACEPLATE FROM THE EXISTING SWITCH.
 - UNSCREW THE SWITCH FROM THE ELECTRICAL BOX AND GENTLY PULL IT OUT.
2. **INSPECT WIRES:** EXAMINE THE WIRES CONNECTED TO THE EXISTING SWITCH. TYPICALLY, YOU WILL FIND:
 - A BLACK (HOT) WIRE
 - A WHITE (NEUTRAL) WIRE
 - A GREEN OR BARE (GROUND) WIRE

IF THERE ARE ADDITIONAL WIRES, TAKE NOTE OF THEIR CONNECTIONS AS YOU WILL NEED TO REPLICATE THEM WITH THE NEW DIMMER SWITCH.

WIRING THE LUTRON DVCL-153P

THE LUTRON DVCL-153P HAS SPECIFIC WIRING REQUIREMENTS. FOLLOW THESE STEPS TO CONNECT THE WIRES CORRECTLY:

1. **IDENTIFY THE WIRES ON THE DIMMER:**
 - THE DIMMER WILL HAVE THREE TERMINALS: ONE FOR THE LOAD (LIGHT), ONE FOR THE LINE (POWER SUPPLY), AND ONE FOR THE GROUND.
 - THE TERMINALS ARE USUALLY LABELED AS FOLLOWS:
 - BLACK TERMINAL: LOAD
 - BLACK WIRE WITH A WHITE STRIPE: LINE
 - GREEN TERMINAL: GROUND
2. **CONNECT THE WIRES:**
 - **GROUND WIRE:** CONNECT THE GREEN OR BARE WIRE FROM THE ELECTRICAL BOX TO THE GREEN TERMINAL ON THE DIMMER. USE A WIRE NUT TO SECURE THE CONNECTION.

- **LINE WIRE:** CONNECT THE BLACK WIRE (HOT) FROM THE ELECTRICAL BOX TO THE BLACK WIRE WITH A WHITE STRIPE ON THE DIMMER. SECURE WITH A WIRE NUT.
- **LOAD WIRE:** CONNECT THE REMAINING BLACK WIRE FROM THE DIMMER TO THE BLACK WIRE LEADING TO THE LIGHT FIXTURE. AGAIN, SECURE THIS CONNECTION WITH A WIRE NUT.

3. **CHECK CONNECTIONS:** ENSURE THAT ALL WIRE CONNECTIONS ARE TIGHT AND NO BARE WIRE IS EXPOSED. THIS WILL HELP PREVENT ANY SHORT CIRCUITS OR ELECTRICAL HAZARDS.

INSTALLING THE DIMMER SWITCH

ONCE THE WIRING IS COMPLETE, IT'S TIME TO INSTALL THE LUTRON DVCL-153P INTO THE ELECTRICAL BOX:

1. **CAREFULLY TUCK WIRES:** GENTLY PUSH THE WIRES BACK INTO THE ELECTRICAL BOX, ENSURING THEY ARE NOT PINCHED OR CRIMPED.
2. **MOUNT THE DIMMER:** ALIGN THE DIMMER SWITCH WITH THE MOUNTING HOLES IN THE ELECTRICAL BOX AND SECURE IT USING THE PROVIDED SCREWS.
3. **ATTACH THE FACEPLATE:** ONCE THE DIMMER IS SECURED, ATTACH THE FACEPLATE BY SNAPPING IT INTO PLACE OR USING SCREWS AS APPLICABLE.

TESTING THE INSTALLATION

AFTER THE INSTALLATION IS COMPLETE, IT'S CRUCIAL TO TEST THE DIMMER SWITCH TO ENSURE IT WORKS CORRECTLY:

1. **TURN THE POWER BACK ON:** HEAD TO YOUR CIRCUIT BREAKER AND TURN THE POWER SUPPLY BACK ON TO THE LIGHT FIXTURE.
2. **TEST THE DIMMER:**
 - FLIP THE DIMMER SWITCH TO THE "ON" POSITION.
 - USE THE DIMMING SLIDER OR DIAL TO ADJUST THE BRIGHTNESS OF THE CONNECTED LIGHTS. MAKE SURE THAT THE DIMMER FUNCTIONS SMOOTHLY AND THAT THERE ARE NO FLICKERING OR BUZZING NOISES.
3. **CHECK FOR OVERLOADING:** IF THE LIGHTS FLICKER, TURN OFF THE DIMMER IMMEDIATELY AND CHECK THE BULB COMPATIBILITY AND LOAD LIMITS TO ENSURE YOU ARE NOT EXCEEDING THE DIMMER'S MAXIMUM WATTAGE.

TROUBLESHOOTING COMMON ISSUES

IF YOU ENCOUNTER ISSUES AFTER INSTALLATION, CONSIDER THE FOLLOWING TROUBLESHOOTING TIPS:

1. **FLICKERING LIGHTS:** IF THE LIGHTS FLICKER WHEN DIMMED:
 - ENSURE THAT YOU ARE USING COMPATIBLE LED OR CFL BULBS. NOT ALL DIMMABLE BULBS WORK WITH EVERY DIMMER.
 - CHECK THAT THE TOTAL WATTAGE OF THE BULBS DOES NOT EXCEED THE DIMMER'S CAPACITY.
2. **DIMMER NOT FUNCTIONING:** IF THE DIMMER DOES NOT RESPOND:
 - CONFIRM THAT THE POWER SUPPLY IS ON.
 - DOUBLE-CHECK ALL WIRE CONNECTIONS FOR SECURITY AND CORRECTNESS.
3. **OVERHEATING:** IF THE DIMMER FEELS HOT:
 - ENSURE THAT YOU ARE USING THE CORRECT WATTAGE BULBS.
 - MAKE SURE THE DIMMER IS NOT OVERLOADED.

MAINTENANCE AND CARE

TO ENSURE THE LONGEVITY AND PERFORMANCE OF YOUR LUTRON DVCL-153P DIMMER SWITCH, REGULAR MAINTENANCE IS KEY:

1. **KEEP CLEAN:** DUST THE FACEPLATE REGULARLY TO PREVENT DUST ACCUMULATION, WHICH CAN AFFECT PERFORMANCE.
2. **CHECK CONNECTIONS:** PERIODICALLY INSPECT THE WIRING CONNECTIONS, ESPECIALLY IF YOU NOTICE ANY PERFORMANCE ISSUES. LOOSE CONNECTIONS CAN LEAD TO ELECTRICAL PROBLEMS.
3. **REPLACE BULBS PROMPTLY:** IF A BULB BURNS OUT, REPLACE IT PROMPTLY TO AVOID PUTTING EXTRA STRAIN ON THE DIMMER SWITCH.

CONCLUSION

INSTALLING THE LUTRON DVCL-153P DIMMER SWITCH CAN GREATLY ENHANCE YOUR LIGHTING EXPERIENCE, ALLOWING FOR CUSTOMIZABLE AMBIANCE THROUGHOUT YOUR HOME. BY FOLLOWING THESE DETAILED INSTALLATION INSTRUCTIONS, SAFETY PRECAUTIONS, AND TROUBLESHOOTING TIPS, YOU CAN ENSURE A SUCCESSFUL INSTALLATION. ENJOY THE FLEXIBILITY OF DIMMABLE LIGHTING, AND REMEMBER TO FOLLOW PROPER MAINTENANCE PRACTICES TO KEEP YOUR DIMMER SWITCH FUNCTIONING CORRECTLY FOR YEARS TO COME.

FREQUENTLY ASKED QUESTIONS

WHAT IS THE FIRST STEP IN INSTALLING THE LUTRON DVCL-153P DIMMER SWITCH?

THE FIRST STEP IS TO TURN OFF THE POWER AT THE CIRCUIT BREAKER TO ENSURE SAFETY DURING INSTALLATION.

DO I NEED ANY SPECIAL TOOLS TO INSTALL THE LUTRON DVCL-153P?

YOU WILL NEED A SCREWDRIVER AND POSSIBLY WIRE STRIPPERS FOR THE INSTALLATION OF THE LUTRON DVCL-153P DIMMER SWITCH.

CAN I INSTALL THE LUTRON DVCL-153P IN A 3-WAY SWITCH CONFIGURATION?

YES, THE LUTRON DVCL-153P CAN BE USED IN A 3-WAY CONFIGURATION, BUT YOU WILL NEED A COMPATIBLE 3-WAY SWITCH.

WHAT TYPE OF BULBS ARE COMPATIBLE WITH THE LUTRON DVCL-153P?

THE LUTRON DVCL-153P IS COMPATIBLE WITH DIMMABLE LED, CFL, INCANDESCENT, AND HALOGEN BULBS.

HOW DO I CONNECT THE WIRES WHEN INSTALLING THE LUTRON DVCL-153P?

CONNECT THE BLACK WIRE FROM THE DIMMER TO THE BLACK (HOT) WIRE IN THE WALL, THE WHITE WIRE TO THE WHITE (NEUTRAL) WIRE, AND THE GREEN WIRE TO THE GROUND WIRE.

IS THERE A SPECIFIC ORIENTATION FOR THE LUTRON DVCL-153P WHEN INSTALLING?

YES, ENSURE THE DIMMER IS INSTALLED IN THE UPRIGHT POSITION FOR PROPER FUNCTIONALITY.

WHAT SHOULD I DO IF THE LUTRON DVCL-153P DOES NOT WORK AFTER

INSTALLATION?

FIRST, CHECK THAT THE POWER IS ON AT THE CIRCUIT BREAKER, THEN ENSURE ALL WIRE CONNECTIONS ARE SECURE AND CORRECT. IF PROBLEMS PERSIST, CONSULT THE TROUBLESHOOTING SECTION IN THE MANUAL.

Find other PDF article:

<https://soc.up.edu.ph/43-block/pdf?docid=gXw06-3342&title=nihs-certification-test-answers.pdf>

Lutron Dvcl 153p Installation Instructions

Lutron Support Community

Aug 26, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Activity Stream - Lutron Support Community

Aug 13, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Welcome to the Lutron Support Community

Welcome to the Lutron Support Community Residential Systems HomeWorks QSX RadioRA 3 RadioRA 2 Caseta Wireless Shading Solutions Shading Solutions - Shades LED Solutions ...

Forum: Troubleshooting - RA3 - forums.lutron.com

Aug 12, 2024 · Sticky: How to OOB or Change a Picos Frequency Started by Austin P., 06-14-2022 04:47 PM Replies: 3 Views: 13,048 miked212 08-17-2022, 09:51 PM

Search Results - Lutron Support Community

Aug 13, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Forum: Troubleshooting - RA2 - forums.lutron.com

Oct 13, 2024 · Sticky: How to OOB or Change a Picos Frequency Started by Austin P., 06-14-2022 04:47 PM Replies: 0 Views: 11,132 Austin P. 06-14-2022, 04:47 PM

Forum: Troubleshooting - RA2 - forums.lutron.com

Oct 13, 2024 · Sticky: Main repeater LED blink codes Started by Ty W., 07-03-2013 11:42 AM 2 Pages • 1 2 Replies: 19 Views: 271,930 Kilowatt 10-21-2019, 05:44 PM

Programming - Vive - forums.lutron.com

Feb 2, 2024 · Quick Navigation Programming - Vive Top HomeWorks QSX RadioRA 3 RadioRA 2 Caseta Wireless Shading Solutions - Shades LED Solutions Quantum Vive Standalone Energi ...

RadioRA 3 - forums.lutron.com

Oct 14, 2024 · Discuss RadioRA 3, the wireless total home control system that gives you the ability to control lighting and shades throughout your home.

HomeWorks QSX - forums.lutron.com

Sep 20, 2024 · Discuss HomeWorks QSX, capable of RF as well as wired system communication for new construction and retrofit applications.

Lutron Support Community

Aug 26, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Activity Stream - Lutron Support Community

Aug 13, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Welcome to the Lutron Support Community

Welcome to the Lutron Support Community Residential Systems HomeWorks QSX RadioRA 3 RadioRA 2 Caseta Wireless Shading Solutions Shading Solutions - Shades LED Solutions ...

Forum: Troubleshooting - RA3 - forums.lutron.com

Aug 12, 2024 · Sticky: How to OOB or Change a Picos Frequency Started by Austin P., 06-14-2022 04:47 PM Replies: 3 Views: 13,048 miked212 08-17-2022, 09:51 PM

Search Results - Lutron Support Community

Aug 13, 2024 · Connect and collaborate with other Lutron customers in the Lutron Support Community to discover solutions and share tips on Lutron products and systems.

Forum: Troubleshooting - RA2 - forums.lutron.com

Oct 13, 2024 · Sticky: How to OOB or Change a Picos Frequency Started by Austin P., 06-14-2022 04:47 PM Replies: 0 Views: 11,132 Austin P. 06-14-2022, 04:47 PM

Forum: Troubleshooting - RA2 - forums.lutron.com

Oct 13, 2024 · Sticky: Main repeater LED blink codes Started by Ty W., 07-03-2013 11:42 AM 2 Pages • 1 2 Replies: 19 Views: 271,930 Kilowatt 10-21-2019, 05:44 PM

Programming - Vive - forums.lutron.com

Feb 2, 2024 · Quick Navigation Programming - Vive Top HomeWorks QSX RadioRA 3 RadioRA 2 Caseta Wireless Shading Solutions - Shades LED Solutions Quantum Vive Standalone Energi ...

RadioRA 3 - forums.lutron.com

Oct 14, 2024 · Discuss RadioRA 3, the wireless total home control system that gives you the ability to control lighting and shades throughout your home.

HomeWorks QSX - forums.lutron.com

Sep 20, 2024 · Discuss HomeWorks QSX, capable of RF as well as wired system communication for new construction and retrofit applications.

Discover essential Lutron DVCL 153P installation instructions for a seamless setup. Enhance your lighting experience today—learn more with our step-by-step guide!

[Back to Home](#)